



FM (Single Channel) Preselector

3634FM Tunable Bandpass Filters



Typical Frequency Response of 3634FM

3634FM Series

This high "Q" FM preselector isolates the desired channel from unwanted interference. Three self-locking tuning adjustments provide full FM tunability in the field. Factory tuned to your channel at no additional charge.

Specifications:

3 dB bandwidth	350 KHz \pm 10%
Insertion Loss at Tuned Frequency	5 dB Max
Rejection	20 dB Min \pm 800 KHz
Return Loss	14 dB Min

Mechanical Specifications:

Baseplate Dimensions: 10" x 4.5"
Rack Mount Available Upon Request
Connectors: F-female (Std.); N, SMA or BNC-female (Opt.)
Impedance: 75 Ohm (Std.); 50 Ohm (Opt.)

Ordering Information:

3634(X)(Y) - (Fo)

- (X) = Female Connector Type
 - = (No Designation) F
 - = (B) BNC, (S) SMA or (N) N
- (Y) = Impedance
 - = (No Designation) 75 Ohm
 - = (50) 50 Ohm



MICROWAVE FILTER COMPANY, INC.

6743 Kinne Street, East Syracuse, NY 13057 • Toll Free: 800-448-1666 or 888-206-6610
www.microwavefilter.com • email: mfcsales@microwavefilter.com • International: 315-438-4700