

BRS/EBS/MMDS (2.5-2.7 GHz) Channels Allocation

Channel	Frequency Allocation (MHz)	
BRS1	2496-2502	
A1	2502-2507.5	WIMAX Channels Allocation (Wireless Internet Providers)
A2	2507.5-2513	
A3	2513-2518.5	
B1	2518.5-2524	
B2	2524-2529.5	
B3	2529.5-2535	
C1	2535-2540.5	
C2	2540.5-2546	
C3	2546-2551.5	
D1	2551.5-2557	
D2	2557-2562.5	
D3	2562.5-2568	
J	2568-2572	
A4	2572-2578	Educational TV Channels Allocation (Universities, Medical Institutes)
B4	2578-2584	
C4	2584-2590	
D4	2590-2596	
G4	2596-2602	
F4	2602-2608	
E4	2608-2614	
K	2614-2618	
BRS2	2618-2624	
E1	2624-2629.5	WIMAX Channels Allocation (Wireless Internet Providers)
E2	2629.5-2635	
E3	2635-2640.5	
F1	2640.5-2646	
F2	2646-2651.5	
F3	2651.5-2657	
H1	2657-2662.5	
H2	2662.5-2668	
H3	2668-2673.5	
G1	2673.5-2679	
G2	2679-2684.5	
G3	2684.5-2690	

Broadcast Auxiliary Services (BAS) Channels Allocation

Channel	Center (MHz)	Allocation (MHz)
A 1	2031.5	2025.5 – 2037.5
A 2	2043.5	2037.5 – 2049.5
A 3 :	2055.5	2049.5 – 2061.5
A 4	2067.5	2061.5 – 2073.5
A 5	2079.5	2073.5 – 2085.5
A 6	2091.5	2085.5 – 2097.5
A 7:	2103.5	2097.5 – 2109.5



MICROWAVE FILTER COMPANY, INC.

6743 Kinne Street, East Syracuse, NY 13057 • Toll Free: 800-448-1666 or 888-206-6610

www.microwavefilter.com • email: mfcsales@microwavefilter.com • International: 315-438-4700